

Eski Seri Dunlop DVR NVR IP Kameralarda Şifre Resetleme İşlemi

Sadp programından şifre resetleme işlemi yapacağımız kamerayı seçerek seri numarasını kopyalıyoruz. Daha sonra <https://ipcamtalk.com/pages/hikvision-password-reset-tool/> sitesinde açılan sayfaya seri numarası ve cihaz start time bilgilerini girerek ekranın altından çıkan **password reset code** sekmesinde çıkan kod numarasını kopyalayarak SADP programından sağ alt köşede yer alan Forgot Password yazan sekmeye tıklayarak yapıyoruz. Password is recovered ekranından sonra şifre 12345 olarak değişecektir.

Hikvision Camera Password Reset Utility

This tool will generate a **password reset code** which you may use to reset a forgotten admin password for a Hikvision camera.

Enter your camera's complete CASE SENSITIVE serial number, as seen in the Hikvision SADP tool:

Important: The date you enter below must match with the camera's clock. **Most likely it is not today's date!** To find out what date your camera thinks it is, power cycle your camera, give it time to boot up, and then refresh your camera list in SADP and check the Start Time column.

Enter the **4 digit** year the camera thinks it is:

Enter the **2 digit** month the camera thinks it is:

Enter the **2 digit** day the camera thinks it is:

Your **password reset code** will appear below.

qdzdSQSSdR

The code must be entered into the Hikvision SADP tool in the **Serial code** box (called **Security Code** in later SADP versions). The camera will compare its internal date and time with the date and time you have entered above. The Serial Number and date must match perfectly or else the code will not work.

Tool created by bp2008. Discussion thread here.

SADP

Total number of online devices: 7

ID	Device Type	Status	IPv4 Address	Port	Software Version	IPv4 Gateway	HTTP Port	Device
001	DP-2716NI-I4	Active	10.0.0.196	8101	V4.1.50build.180...	10.0.0.254	80	DP-2
002	DP-2604NI-K1/4P	Active	10.0.0.249	8000	V3.4.98build.171...	10.0.0.254	80	DP-2
003	DP-M2504HNJ-GLF/WI	Active	10.0.0.192	8000	V4.1.1build.180814	10.0.0.254	80	DP-2
004	DP-22CD6510D-IO	Active	10.0.0.2	8000	V5.4.5build.1710...	10.0.0.254	80	DP-2
005	DP-22DV9188-A1A	Active	10.0.0.196	8000	V4.1.1build.180814	10.0.0.254	80	DP-2
006	DP-2104NI-SN/P	Active	10.0.0.196	8000	V4.1.1build.180814	10.0.0.254	80	DP-2
007	DP-22D1T32-18	Active	192.0.0.64	8000	V4.1.1build.180814	10.0.0.254	80	DP-2

Modify Network Parameters

Enable DHCP
Enable Hik-Connect

Device Serial No.: T32-1820151216CCWR561836885

IP Address: 192.0.0.64

Port: 8000

Subnet Mask: 255.255.255.0

Gateway: 0.0.0.0

IPv6 Address: ::

IPv6 Gateway: ::

IPv6 Prefix Length: 0

HTTP Port: 80

Security Verification

Admin Password:

Modify

Forgot Password

Restore Default Password

Security Code:

Confirm Cancel

Restore Default Password

Security Password is recovered.

Confirm Cancel

NOT: Şifre resetleme işlemi start time bilgisi esas alınarak yapıldığından kamerayı kapatıp açtıktan sonra güvenlik kodunu girmeniz gerekmektedir.